



Product name: 20A brushed ESC

Suitable for 1/16, 1/18, 1/24 remote control climbing car military truck semi-big truck modification, remote control boat, The light weight is also suitable for mini-Z mosquito car modification

Function: forward, reverse, brake

Working voltage: 4.8V–8.4V (suitable for 2S lithium battery)

Current (A): 20A

Drive frequency: 2kHz

Input: Li Po 2S/Ni-MH/Ni-Cd 4-7 battery

Constant current: 20A, 25A<30s pulse 50A<5s

UBEC output: voltage 5.7V, current 1A

This ESC can be matched with 130/180/260/280/380 brush motor

Adjustment: The ESC is in the middle range, the new controller needs to fine-tune the throttle, so that the ESC light does not light up, keep it on Neutral, controlled throttle trim is TH TRIM

Weight: 8g

From:

<https://kornequipped.com/mywiki/> - **KornEquipped**

Permanent link:

https://kornequipped.com/mywiki/doku.php?id=20a_rc_speed_control

Last update: **2026/01/30 22:52**

